A combination of the TDM with the SRQAM of the present invention has been described in the above. However, the SRQAM of the present invention can be combined also with any of the FDM, CDMA and frequency dispersal communications systems.

What is claimed is:

1. A signal transmission and reception apparatus for transmitting and receiving an n-level VSB signal, the apparatus comprising a transmitter and a receiver;

said transmitter comprising

a compression means for compressing an input video 10 signal to a digital video compression signal;

- an error correction encoding means for adding an error correction code to the digital video compression signal to produce an error correction coded signal;
- a modulation means for modulating the error correction 15 coded signal to an n-level VSB modulation signal, said modulation means comprising a means for allocating code points along a uniaxial modulation coordinate system, and a filter means having a plurality of coefficients which are a series of impulse 20 responses defined by plotting timebase responses to the VSB modulation signal along the in-phase axis and its orthogonal axis for filtering a series of said code points allocated along the uniaxial modulation coordinate system; and

a transmission means for transmitting the modulation signal, and

said receiver comprising

a means for receiving a transmitted n-level VSB modulation signal;

a demodulation means for demodulating the received 30 n-level VSB modulation signal into a digital reception signal;

an error correction means for error correcting the digital reception signal to obtain an error-cor-rected digital signal; and

an expanding means for expanding the error-corrected digital signal to obtain a video output signal.

2. A transmission and reception apparatus according to claim 1, wherein the error correction means comprises a 40 trellis decoder.

3. A transmission and reception apparatus according to claim 2, wherein the trellis decoder is associated with a plurality of memories which each holds a number of selectable correct codes.

4. A transmission and reception apparatus according to claim 1, wherein the digital reception signal is divided into a high priority signal and a low priority signal, and wherein said error correction means comprises a high code gain first error correction means and a low code gain second error correction means, said first error correction means correct- 50 ing the high priority signal.

5. A transmission and reception apparatus according to claim 4, wherein the high priority signal carries the address

data for all data

- 6. A transmission and reception apparatus according to claim 4, wherein the first error correction means comprises 55 a trellis decoder.
- 7. A signal transmission and reception apparatus according to claim 1, further comprising a band path filtering means for filtering the n-level VSB modulation signal before being transmitted.

8. A signal transmission and reception apparatus for transmitting an n-level VSB signal, comprising:

- a compression means for compressing an input video signal into a digital video compression signal;
- an error correction encoding means for adding an error 65 correction code to the digital video compression signal to produce an error correction coded signal;

- a modulation means for modulating the error correction coded signal to an n-level VSB modulation signal, said modulation means comprising a means for allocating code points along a uniaxial modulation coordinate system, and a filter means having a plurality of coef-ficients which are a series of impulse responses defined by plotting time tase responses to the VSB modulation signal along the in-phase axis and its orthogonal axis for filtering a series of said code points allocated along the uniaxial modulation coordinate system; and
- a transmission means for transmitting the modulation signal.
- 9. A signal transmission apparatus according to claim 8, further comprising a band path filtering means for filtering the n-level VSB modulation signal before being transmitted. 10. A signal receiving apparatus comprising:
 - a tuner for receiving a transmission signal containing a digital modulation signal and an analog modulation signal and for selecting the digital modulation signal using a local oscillation signal;

an interference detecting means for detecting interference caused by the analog modulation signal from the digital modulation signal selected by the tuner;

a notch filter means responsive to the interference detected by the interference detecting means for removing a carrier of the analog modulation signal in a same frequency band as a frequency band of the digital modulation signal;

an error ratio calculating means for calculating a bit error ratio of an output of the notch filter means; and

an automatic frequency correcting means for changing a frequency of the local oscillation signal of the tuner according to a level of the interference detected by the interference detecting means and the bit error ratio calculated by the error ratio calculating means to com-

pensate for a frequency offset of the carrier of the analog modulated signal.

11. A signal receiving apparatus according to claim 10, wherein the digital modulation signal is an n-level VSB modulation signal.

- 12. A signal receiving apparatus comprising: a tuner for ecciving a ransmission signal containing at least one of a VSB modulated signal and a QAM modulated signal and for selecting one of the VSB modulated signal and the QAM modulated signal to obtain a selected signal;
- an analog-to-digital converter for converting the selected signal into a series of digital codes;
- a transversal filter provided on an orthogonal axis for suppressing a transmission distortion of the series of digital codes with respect to both orthogonal axes to obtain a series of filtered digital codes allocated on the orthogonal axes;
- a carrier recovery means for phase-compensating a carrier of the filtered digital codes allocated on the orthogonal axis outputted from the transversal filter; and
- a control means for producing a control signal to extract detected codes at equal time intervals from the VSB modulated signal;
- a clock reproducing means for phase synchronizing entire codes of the QMM modulated signal when the selected signal is the QAM modulated signal and for phase synchronizing codes of the VSB modulated signal intermittently at predetermined intervals when the selected signal is the VSB modulated signal; and
- a decoding means for decoding an output of the carrier recovery means.